## **WALL OUTLET**

## SAT/TV/FM WALL OUTLET





MODEL		A3101T-3AA	A3110-3AA (Loop)
THRU LOSS (dB max.)	5-2300MHz	-	3.5
IN – RADIO TAP LOSS (dB)	88-108MHz	1.8	13
IN – TV TAP LOSS (dB)	5-30MHz	1.4	10
	47-68MHz	1.4	10
	125-470MHz	1.4	10
	470-862MHz	1.8	10
IN – SAT TAP LOSS (dB)	950-2300MHz	2.3	13
RETURN LOSS (dB min.)		6	6
DIMENSION (mm)		70 x 66 x 32.3	
WEIGHT (g)		100	

- RFI shielded zinc die-casting housing.
  Screening efficiency fulfils CENELEC 50083-2: 1988, Class A
  F-female connector for Sat, IEC connector male for TV and female for Radio
  Power passing: 24VDC, 0.5A, IN ↔ SAT.

Specifications are subject to change without notice.