Data Sheet



UBB amplifiers AMP9763



UBB (ultra broadband) line amplifiers with return path. To be used as the final amplifier before wall outlets. Normally used to amplify the signals after an optical link. All adjustments are internally located under the die cast cover secured with safety screws to prevent unauthorised access. Packaging 1 pc.

Key Points


- Operating temperature: -10 to +55°C.
- Gain and slope adjustment in TV and SAT band
- Female F connectors
- Passive or active return path, switchable by the installer

			AMP9763	
Code		·	235052	
Bandwidth	MHz	5-30	47-862	950-2400
Gain	dB	25	40	40
Flatness	dB	<u>+2</u>	<u>+2</u>	±2
Gain adjustment	dB	-	0-20	0-20
Slope adjustment	dB	-	0-20	0-20
Max. output level				
IM3-60 dB 3 unequal tones	dBµV	100	120	-
IM3-54 dB 2 unequal tones	dBµV	100	120	-
IM3-52 dB 3 equal tones	dBµV	98	118	-
IM3-60 dB 3 equal tones	dBµV	94	114	-
IM3-60 dB 2 equal tones	dBµV	97	117	-
IM2-60 dB 2 equal tones	dBµV	95	115	-
IM2-35 equal tones	dBµV	-	-	125
General Parameters				
Noise figure	dB	3	8	10
Conectors			F	
Impedance	Ohm		75	
Test point	dB		-30	
Mains voltage	Vac, Hz		220-240, 50-60	
Power consumption	VV		16	
Protection index			IP20	
Dimensions (L.×H.×D.)	mm		194x143x63	
Operating Temperature	°C		-10 to +55	

Data Sheet



Basic installation systems



AMP9763

Installation example

Fracarro Radioindustrie S.p.A. Via Cazzaro, 3 31033 Castelfranco Veneto (TV) Italy tel. +39 0423 7361 fax +39 0423 736220 www.fracarro.com info@fracarro.com Fracarro (UK) Ltd Unit A. Ibex House, Keller Close Kilin Farm, Milton Keynes. MK11 3LL UK Tel. +44(0)1908 571571 Fax +44(0)1908 571570 Fracarro Ibérica Poligono Táctica "Ciudad de los negocios" C/2A, n° 4 - 46980 Paterna - Valencia Tel. +34/961340104 Fax, +34/961340691

Fracarro France S.A.S. 14 bis rue du Ratrait 92158 Suresnes Cedex France Tel. +33 1 47283400 Fax +33 1 47283421 Fracarro Tecnologia e Antenas de Televisao Lda Rua Alexandre Herculano, n°1–1°B Edificio Central Park 2795-242 Linda-a-Velha Portugal Tel.: +351214156800 Fax: +351214156809

FRACARRO

Fracarro Radioindustrie S.p.A. via Cazzaro, 3 31033 Castelfranco Veneto (TV) italy tel. +39 0423 7361 fax +39 0423 736220 www.fracarro.com info@fracarro.com Fracarro (UK) Ltd Unit A. Ibex House, Keller Close Kilin Farm, Milton Keynes. MK11 3LL UK Tel. +44(0)1908 571571 Fax +44(0)1908 571570 Fracarro Ibérica Poligono Táctica "Ciudad de los negocios" C/2A, n° 4 - 46980 Paterna - Valencia Tel. +34/961340104 Fax. +34/961340691

Fracarro France S.A.S. 14 bis rue du Ratrait 92158 Suresnes Cedex France Tel. +33 1 47283400 Fax +33 1 47283421

Fracarro Tecnologia e Antenas de Televisao Lda Rua Alexandre Herculano, n''i-1''B Edifício Central Park 2795-242 Linda-a-Velha Portugal Tel.: +351214156800 Fax: +351214156809

www.fracarro.com